



Seed Treatment Instructions

Seed-Start™ & Nutri-Life BAM™

Mixing & Application Details

Cereals – e.g. wheat , barley, oats, sorghum, millet, corn

Legumes – e.g. chickpeas, faba beans, mung beans, soybeans, lupins

Oilseeds – e.g. canola, linseeds, sunflower

Brassicas – e.g. tillage radish, forage rape, turnips, kale & swedes

Application Rates*:

Crop	BAM™	Seed-Start™
Small Seeds	Up to 4 L/tonne	8 L/tonne
Medium Seeds	Up to 4 L/tonne	8 L/tonne
Large Seeds	Up to 4 L/tonne	6 L/tonne

Mixing Instructions:

- 1 Add Nutri-Life BAM™ and Seed-Start™ together and mix thoroughly.
- 2 Legume inoculants may be pre-mixed and added at this stage.
- 3 Apply to seed.

Application:

***Volume:** Total mixture should be enough to just coat the seed (~12 L/tonne wheat seed).

Agitation: Constant agitation is required during application to keep the mixture even and to prevent products from settling out.

Timing: Can be applied several days prior to planting. Allow time (> 2 hours) for the seed to dry before adding to the seed box or air seeder – failure to do so may alter seeding rate.

Compatibilities: Compatible with commercial *Rhizobia* inoculants.

**Nutrition
Farming®**

Contact NTS for
more information.

Ph: 07 5472 9900
www.nutri-tech.com.au