



Seed Treatment Instructions

Seed-Start™ & Platform® Mixing & Application Details

Cereals – e.g. wheat, barley, oats, sorghum, millet, corn

Legumes – e.g. chickpeas, faba beans, mung beans, soybeans

Application Rates:

- **Platform®** 1 kg/tonne seed
- **Seed-Start™** 5 L/tonne seed

**Nutrition
Farming®**

Contact NTS for more
information.

Ph: 07 5472 9900
www.nutri-tech.com.au

Mixing Instructions For Every 1 Tonne Of Seed:

- 1 Pre-wet the **Platform®** powder in enough water to make a flowable paste, i.e. around 1 kg Platform® to 4-5 L water.
- 2 Mix thoroughly.
- 3 Slowly add 5 L **Seed-Start™** to the **Platform®** mixture whilst mixing.
- 4 Legume inoculants (e.g. freeze-dried) may be pre-mixed and added at this stage.
- 5 Apply to seed.

Application:

Volume: Total mixture should be enough to just coat the seed (~10 L/tonne wheat seed).

Agitation: Constant agitation is required during application to keep the mixture even and to prevent products from settling out.

Filter Size (if applicable): Platform® spore sizes can be up to 260 µm (0.26 mm) therefore 30 mesh (0.595 mm) is recommended.

Timing: Can be applied several days prior to planting. Allow time (> 2 hours) for the seed to dry before adding to the seed box or air seeder – failure to do so may alter seeding rate.

Compatibilities: Compatible with commercial Rhizobia inoculants. See [current compatibility](#) list for Platform® (live fungi spores) and fungicides/pesticides, for pre-treated seeds.